

B05 | Bluetooth Remote Speaker Microphone



Default button features when using iConvNet PTT app

- | | |
|--|---|
| 1 Power/play/pause/reject calls | 8 Page down button |
| 2 PTT button | 9 Disconnect/Reconnect Bluetooth |
| 3 Customizable button - no default function | 10 Group change |
| 4 SOS button | 11 USB Type-C charging port |
| 5 Indicator light | 12 Volume up |
| 6 OK button | 13 Volume down |
| 7 Page up button | 14 QR code for easy pairing |



Cleaning and Maintenance

- Before cleaning and maintaining the device: please stop running, turn off the device, and disconnect all connections with other equipment.
- When you do not use the radio, please cover the accessories connector.
- When cleaning the dust, please use soft brush and neutral detergent (no strong corrosive chemicals) to wipe it.
- Please keep the equipment and accessories dry.
- Please do not use the microwave oven or hair dryer or other heating devices to dry them.

Standard Accessories



Hand Strap
Hand Strap



ACUSBA
Wall Adapter



USBA-MR
Micro USB Cable



BC-S380
Belt Clip

General

Compatibility	Android, iOS	Battery	3500 mAh
Bluetooth Version	BT 5.1	Dimension	90.9x63x30.5mm (without antenna and belt clip)
Bluetooth Protocol	HFP HSP A2DP AVRCP SPP BLE	Weight	192g
Wireless Transmission Range	>10m	Working Temperature	-10°C (~ 60°F)
Headset Integration	TYPE-C, Supports air duct headphones	Storage Temperature	-20°C (~ 70°F)

Certification

Transmitter Frequency:	BT:	2402-2480MHz	Receiver Frequency:	BT:	2402-2480MHz
	BLE:	2402-2480MHz		BLE:	2402-2480MHz NFC: 13.56MHz
RF-Output Power: ERP/EIRP/Conducted	BT:	8.58dBm			
	BLE:	7.95dBm			