

T521 | 4G Portable Push to talk over Cellular Radio



Default button features when using iConvNet PTT app

- | | |
|--|---|
| 1 <i>Short press:</i> Account status
<i>Long press:</i> Version # | 5 Group selector |
| 2 PTT button | 6 Power/Volume |
| 3 <i>Short press:</i> Last message/select
<i>Long press:</i> Individual call | 7 Microphone |
| 4 <i>Short press:</i> Group & User name
<i>Long press:</i> Battery level | 8 Panel cover for speaker microphone port. <i>Unscrew, then attach speaker microphone.</i> |

Please note: The Inrico T521 PoC radio does not support the installation of third-party apps and is exclusively compatible with its native iConvNet RTOS, specifically designed for this device. **Enjoy a 1-year FREE subscription to the RTOS from the time of purchase. After the first year, the subscription costs \$40 annually.**
Learn more: inrico.ca/ptt-app

Standard Accessories



Optional Accessories



Connection

Frequencies	GSM: B2/3/5/8 WCDMA: B1/2/4/5/8 FDD-LTE: B1/2/3/4/5/7/8/20/28/66 TDD-LTE: B38/39/40/41
Navigation	GPS, GLONASS

OS

Operating System	RTOS
-------------------------	------

Certification

Ingress Protection	IP66
Drop	1.2 Meters
Certification	CE/FCC/ROHS

Hardware

RAM+ROM	48MB + 128MB
USB	Micro USB 2.0
Card Slot	Nano Single Card
Interface	K head
Speaker	Ø40mm, 8Ω 3W
Battery	4,800mAh
Talk Time	25 hours
Standby Times	35 hours
Weight	≈308g
Dimension (H*W*D)	141.2 x 64.3 x 38.5mm (Without Antenna and Belt clip)