



Inrico S200 4G PoC Radio

Terminal Default Buttons using iConvNet PTT App



version 7

Guide

- Short press
- Long press
- Rotate



Tested Accessories

- SPM-M3**
Inrico Value Speaker Microphone
- RSM-300-M3**
Wirox Inrico Universal Speaker Microphone
- DT-S200**
Desktop Charging Base for S200
- EPM-M3**
Inrico Earpiece with Acoustic Tube
- B01**
Inrico Bluetooth Microphone
- BP01**
Inrico Bluetooth PTT Button

iConvNet™

Please note: Inrico PoC radios offer programmable buttons, allowing customization for different functions and requirements through the iConvNet PTT App. Keep in mind that the button configurations may vary when using alternative apps.

Connection

Canada and US Version	GSM: B2/B3/B5/B8 WCDMA: B1/B2/B5/B8 TDD-LTE: B38/B40 FDD-LTE: B2/B4/B5/B7/ B12/B13/B17/B26/B28A/B 28B/B66
Wi-Fi	IEEE 802.11 a/b/g/n (2.4G & 5G)
Bluetooth	BT4.0
Navigation	GPS, GLONASS, BEIDOU
NFC	Support

Hardware

CPU	MT6739V/WA
RAM + ROM	2GB+ 32GB
Expand Memory	Optional, up to 128G
Card Slot	Dual Micro SIM card + TF card
USB Port	Micro USB
Interface	M3
Screen Size	3.1 inches, 480*800
Camera	Front Camera 2.0MP, Rear Camera 13.0MP
Speaker	Ø32mm, 8Ω 2W
Microphone	Main MIC + Sub MIC
Battery	3800mAh
Working Times	16 Hours (5/5/90 standard test)
Standby Times	23 Hours
Dimension (H*W*D)	128.0 x 57.0 x 24.5mm (Without Antenna and Belt clip)
Weight	≈210g
Working Temp.	-10°C ~ 60°C
Storage Temp.	-20°C ~ 70°C
Flashlight	Support

Certification

Ingress Protection	IP54
Drop	1.2 Meter
Certification	3C/CTA/CE/ROHS/FCC/CMIT ID:2021CP6739