



Inrico T620 4G PoC Radio

Terminal Default Buttons using iConvNet PTT App



version 7.1

Guide

- Short press
- Long press
- Rotate



iConvNet™

Please note: Inrico PoC radios offer programmable buttons, allowing customization for different functions and requirements through the iConvNet PTT App. Keep in mind that the button configurations may vary when using alternative apps.

Tested Accessories



SPM-M3
Inrico Value Speaker Microphone



RSM-300-M3
Wirox Inrico Universal Speaker Microphone



RSM-400-M3
Wirox IP67 Inrico Universal Speaker Microphone



MC-T6
Multi-Unit Charger



DT-T6
T620/T640A Desktop Charger



EPM-M3
Inrico Earpiece with Acoustic Tube



EM-3229A-M3/SC/1W
Wirox Inrico T522A D-Shape 1-Wire Earpiece



50Q
Wirox Behind The Head Dual Muff Headset
Requires Adapter Cord



QDC-50-M3
Wirox QD Inrico Universal Headset Cable
Option 1: Adapter Cord with PTT



QD-M3
Wirox QD Inrico Universal Headset Cable
Option 2: Adapter Cord

Connection

Canada and US Version	GSM: B2/B3/B5/B8 WCDMA: B2/B4/B5 FDD-LTE: B2/B3/B4/B5/B7/B8/B12/B17/B28a/B28b/B66
Wi-Fi	IEEE 802.11 a/b/g/n, 2.4G & 5G
Bluetooth	BT4.2
Navigation	GPS

Certification

Ingress Protection	IP54
Drop	1 Meter
Certification	CE/FCC/RoHS/3C/CMIT ID:2019CP3612/Appearance patent

Hardware

CPU	MT6739V/WA
RAM + ROM	1GB + 8GB
Card Slot	Micro SIM Card+TF Card
USB	Micro USB 2.0
Interface	M3
Screen Size	1.14 inches, Colour Screen
Speaker	Ø40mm, 8Ω 2W
Battery	4000 mAh
Working Times	17 Hours(5/5/90 standard test)
Standby Time	22 Hours
Dimension (H*W*D)	127 x 63 x 27mm (without antenna and clip)
Weight	≈210g
Working Temperature	-10°C ~ 55°C
Storage Temperature	-20°C ~ 70°C