

S380 | 4G Portable Push to talk over Cellular Radio



Default button features when using iConvNet PTT app

- | | |
|---|---------------------------------|
| 1 Panel cover for speaker microphone port. Unscrew, then attach speaker microphone. | 8 Begin temporary call |
| 2 USB Type-C charging port | 9 Rotate to change group |
| 3 Rear camera and front camera | 10 Volume control knob |
| 4 <i>Short press:</i> Patrol mission
<i>Long press:</i> Listen for app license expiry date | 11 Touch screen |
| 5 PTT button | 12 Power on/off: 3 secs. |
| 6 <i>Short press:</i> Replay last message
<i>Long press:</i> Private call/group call switch | |
| 7 <i>Short press:</i> Listen to name of current group
<i>Long press:</i> Listen for battery level | |

Please note: Inrico PoC radios perform optimally with the iConvNet PTT app. The iConvNet PTT app allows for easy button customization to suit various functions and requirements. Be aware that button configuration may differ when using other PTT apps. [Learn more: inrico.ca/ptt-app](https://www.inrico.ca/ptt-app)

Standard Accessories



Optional Accessories



Connection

Frequencies	2G:	B2/ B3/ B5/ B8
	3G:	B1/ B2/ B4/ B5/ B8
	4G-FDD:	B1/ B2/ B3/ B4/ B5/ B7/ B8/ B12/ B14/ B17/ B20/ B26/ B28/ B66
	4G-TDD:	B38/ B39/ B40/ 41
Wi-Fi	IEEE 802.11 a/b/g/n/ac/k/v/r, 2.4G/5G	
Bluetooth	BT4.0 & BLE5.0	
NFC	Supported	
Navigation	GPS, GLONASS, AGPS	

Certification

Ingress Protection	IP68
Drop	1.5 Meters
Certification	CE/FCC/MIL-STD-810H/GMS

Hardware

RAM+ROM	2GB+16GB
Memory	Expandable up to 128GB
Card Slot	Dual SIM Card+ TF Card
Interface	M6
OTG	Supported via the M6 interface
Screen	2.4 Inches, 480 x 640
Camera	Front camera 5.0MP; Rear camera 13.0MP, wide angle 120°
Speaker	Ø36mm, 8Ω 3W

OS

Operating System	IEEE 802.11 a/b/g/n/ac/k/v/r, 2.4G/5G
------------------	---------------------------------------